



A-SMART HOME

3-buttons changeover light switch

A-NS86-3L2W

POWER CONSUMPTION

Power mode	AC
Voltage	110V ~ 240V
Standby consumption	0.02W
Power consumption	10A
Potencia de carga	800W por segmento / 2000W en total

SPECIFICATIONS (LIGHT SWITCHES)

Backlight	Yes
Electric connection	Only with phase cable
Touch panel	Yes
Status recovery after power failure	Yes
Life cycle	100000 ciclos

MATERIAL AND DIMENSIONS

Dimensions	50 x 50 x 30 mm
Net weight	60 g
Weight with packaging	80 g

AMBIENT

Operating temperature	-20 °C ~ 70 °C
Use	Indoor
Maximum humidity	93%

GENERAL INFORMATION

Type **3-buttons changeover light switch**

